

# PXI-2500 Series

## 4/8-CH 12-Bit 1 MS/s Analog Output Multi-Function PXI modules

### Features

- PXI specifications Rev. 2.0 compliant
- 3U Eurocard form factor, CompactPCI compliant (PICMG 2.0 R3.0)
- 12-bit D/A resolution
- Up to 1MS/s simultaneous-update rate
- 4-CH multiplying analog outputs (PXI-2501)
- 8-CH multiplying analog outputs (PXI-2502)
- Hardware-based arbitrary waveform generation
- On-board 8k-sample D/A FIFO (PXI-2501)
- On-board 16k-sample D/A FIFO (PXI-2502)
- Programmable bipolar or unipolar analog output ranges on per channel basis
- Programmable internal or external reference sources on per channel basis
- 8-CH 400 kS/s 14-bit single-ended analog inputs (PXI-2501)
- 4-CH 400 kS/s 14-bit single-ended analog inputs (PXI-2502)
- On-board 2k-sample A/D FIFO
- Bipolar or unipolar analog input ranges
- Scatter-gather DMA for both analog inputs and outputs
- 24-CH TTL digital input/output
- 2-CH 16-bit general purpose timer/counters
- Analog and digital triggering
- Fully auto calibration
- Multiple modules synchronization through PXI trigger bus

### Operating Systems

- Windows 2000/NT/XP/98
- Red Hat Linux
- Windows CE (call for availability)

### Recommended Software

- VB/VC++/BCB/Delphi
- DAQBench

### Driver Support

- D2K-DASK:
  - Windows 2000/NT/XP/98 driver
- D2K-DASK/X: Red Hat Linux driver
- D2K-LVIEW: LabVIEW driver
- D2K-MTLB: MATLAB driver
- D2K-OCX: 32-bit ActiveX controls



### Introduction

ADLINK PXI-2501 and PXI-2502 are high-speed, high-performance analog output multifunction PXI modules. These devices are able to update up to 8-CH, 12-bit analog outputs simultaneously sustaining 1 MS/s. The reference sources and output polarities are programmable individually per channel. Combine this with the multiplying PXI architecture, ADLINK PXI-2500 series PXI modules can generate complex modulated analog signals. The hardware-based arbitrary waveform generation frees CPU intervention even when all analog outputs are updating at full speed, and the lengths of waveforms are only limited by the system memory.

The PXI-2500 series integrate up to 8-CH, 400 kS/s, 14-bit single-ended analog inputs with programmable polarity, 24-CH programmable digital I/O lines, and 2-CH 16-bit general-purpose timer/counters.

Like all the other members in the PXI-2000 family, the PXI-2500 series is able to perform analog input and output functions at full speed simultaneously. Multiple modules can be synchronized through the PXI trigger bus. The auto-calibration feature adjusts the gain and offset to a specified accuracy, eliminating the need to calibrate the modules by adjusting trim pots.

### Termination Boards

#### DIN-68S/1M

Termination Board with a 68-pin SCSI-II Connector and DIN-Rail Mounting (Including One 1-meter ACL-10568 Cable)



Termination board DIN-68S/1M

### Ordering Information

- **PXI-2501**  
4-CH 12-Bit 1 MS/s Analog Output Multi-Function PXI Module
- **PXI-2502**  
8-CH 12-Bit 1 MS/s Analog Output Multi-Function PXI Module

### Pin Assignment

#### Connector CN1 Pin Assignment

AO_0	1	35	AGND
AO_1	2	36	AGND
AO_2	3	37	AGND
AO_3	4	38	AGND
AOEXTREF_A/AI_0	5	39	AGND
AI_1	6	40	AGND
EXTTRIG/AI_2	7	41	AGND
AOEXTREF_B/AI_3	8	42	AGND
AO_4/AI_4	9	43	AGND
AO_5/AI_5	10	44	AGND
AO_6/AI_6	11	45	AGND
AO_7/AI_7	12	46	AGND
AO_TRIG_OUT_A	13	47	EXTWFTRG_A
AO_TRIG_OUT_B	14	48	EXTWFTRG_B
GPTC1_SRC	15	49	VCC
GPTC0_SRC	16	50	DGND
GPTC0_GATE	17	51	GPTC1_GATE
GPTC0_OUT	18	52	GPTC1_OUT
GPTC0_UPDOWN	19	53	GPTC1_UPDOWN
RESERVED	20	54	DGND
AF11	21	55	AF10
PB7	22	56	PB6
PB5	23	57	PB4
PB3	24	58	PB2
PB1	25	59	PB0
PC7	26	60	PC6
PC5	27	61	PC4
DNGD	28	62	DGND
PC3	29	63	PC2
PC1	30	64	PC0
PA7	31	65	PA6
PA5	32	66	PA4
PA3	33	67	PA2
PA1	34	68	PA0

\* Pin 9~12 are AI<4..7> for PXI-2501 ;  
AO<4..7> for PXI-2502

\* The external references inputs and the external analog trigger share the analog input pins 5, 7, and 8